


MENU MISC




SYSTEM MENU

First power icon button: when enabled, user can power off unit by long pressing REC button in ready state
FLIP SCREEN: 180° screen rotation, used for left-handed or if you prefer that way
AUTO WORKING DAY: when set, do not ask for a new working day at startup, automatically set it
AMBISONIC menu is described into another page



BRIGHTNESS

AMBIENT LIGHT SENSOR: indicates the front panel ambient light sensor (located near the SX-R4+ engraving)
AUTO DIM: when enabled, the backlight and leds intensity are automatically dimmed between minimum and selected intensity according to ambient light.
DISPLAY BACKLIGHT: select this field then set the backlight intensity using the rotary encoder.
SD1/SD2 LEDS: select this field then set the LEDs intensity using the rotary encoder.



SX-RC8+

SX-RC8+ setup page. All parameters concerns the microphone input, which have a gain stage with an automatic level control
MIC SOURCE: internal or external jack
LIMITER GAIN: -54 to +36 dB
LIMITER THRESHOLD:

