


USER SETTINGS



USER SETTINGS MENU


User settings allows user to store & recall a recorder configuration. There are 8 user settings available.

Factory settings (SETUP/SYSTEM/SYSTEM INFO/FACTORY SETTINGS) does not erase user settings.




STORE A USER SETTING

To store a user setting, apply a long press to the selected user setting button until the message "SETTING STORED" is posted.



RECALL A USER SETTING


To recall a user setting, apply a short press to the desired user setting. A confirm window will appear.



MODIFY USER SETTING NAMES

Both lines can be edited.

Press the EDIT NAME to edit first line, press again to edit second line.



USER SETTING CONTENT:

- sampling frequency, bits per sample
- pre-record time
- reference tone level
- SD2 record source (mirror/mix only)
- inputs configuration (type, gain, phase, filter)
- tracks configuration (source, name, arm state, color)
- Phones monitoring
- Outputs monitoring
- Pot configuration (input gain: pot min/max, mute@min, bypass, link or fader curve & assign)
- Meters: reference level (orange, red), range, hold time
- Main screen daylight mode
- WiFi mode
- External power setup: DC out enable, DC in alarm, DC in min, time to empty
- Battery power setup: time to empty
- Push buttons assign